



Let's continue to increase Unit 2 AVR Mvar setpoint in steps of +1 Mvar and display the results on the table below.

Total MW	U1		p.f.	Current	U2		p.f.	Current
	MW	MVARs			MW	MVARs		
56.50	39.55	31.70	0.78	4607.78	16.95	0.00	1.00	1541.01
56.50	39.55	30.70	0.79	4551.48	16.95	1.00	1.00	1543.69
56.50	39.55	29.70	0.80	4496.32	16.95	2.00	0.99	1551.70
56.50	39.55	28.70	0.81	4442.33	16.95	3.00	0.98	1564.96
56.50	39.55	27.70	0.82	4389.56	16.95	4.00	0.97	1583.33
56.50	39.55	26.70	0.83	4338.06	16.95	5.00	0.96	1606.65
56.50	39.55	25.70	0.84	4287.86	16.95	6.00	0.94	1634.69
56.50	39.55	24.70	0.85	4239.02	16.95	7.00	0.92	1667.23
56.50	39.55	23.70	0.86	4191.58	16.95	8.00	0.90	1704.00
56.50	39.55	22.70	0.87	4145.59	16.95	9.00	0.88	1744.74
56.50	39.55	21.70	0.88	4101.11	16.95	10.00	0.86	1789.18
56.50	39.55	20.70	0.89	4058.17	16.95	11.00	0.84	1837.04
56.50	39.55	19.70	0.90	4016.83	16.95	12.00	0.82	1888.06
56.50	39.55	18.70	0.90	3977.14	16.95	13.00	0.79	1942.01
56.50	39.55	17.70	0.91	3939.15	16.95	14.00	0.77	1998.63
56.50	39.55	16.70	0.92	3902.90	16.95	15.00	0.75	2057.72
56.50	39.55	15.70	0.93	3868.46	16.95	16.00	0.73	2119.06
56.50	39.55	14.70	0.94	3835.85	16.95	17.00	0.71	2182.46
56.50	39.55	13.70	0.94	3805.15	16.95	18.00	0.69	2247.75
56.50	39.55	12.70	0.95	3776.38	16.95	19.00	0.67	2314.77

